

Smart AC Bridge Installation Guide



This install guide will walk you through the hardware installation process for the AirTouch **Smart AC Bridge**.

Before Getting Started

Please ensure the AirTouch 5 Main Module has been updated to the latest version.

• From the **AirTouch 5 Console** Home Screen press the *Quick Menu* (top right) then locate the *Update* button under *Settings > Options*

airtouch				* 310	airtoud	ch		Favourites Quick Tir	ner Programs	×
o Lounge	- 24° +		Cool	Medium	Options	System Name:	AT 5 Desk Left	Theme:	Dark	
o Dining	- 100% +		*#*			Suburb:	Gepps Cross, 5094		Set Date Time	
6 Family	- 24° +	Set To	`		Smarts	WiFi:	InternodeEA302D-5G-ext		Display Zone Temp	
💩 Master	- 24° +		1	1 1	Sensors	Local Access	s Login via	Account Only		
o Josh	– Off +				Zones	Save Settings	Terms & Conditions		Update	
💩 Jess	– Off +				Installer	Load Settings	Privacy Policy	Delete Users		

Note: Smart AC Bridge will not function with any version of Main Module firmware earlier than V2.0.0.3

Connecting Smart AC Bridge

After placing **Smart AC Bridge** in range of a Wi-Fi access point, ensure your **AirTouch 5 Main Module** is powered **OFF**. Plug the included (*right latch*) **RJ12 cable** into the port on the **Smart AC Bridge** and then the port on the side of your existing **AirTouch 5 Main Module** labelled **HomeKit** (*next to the RS-485 port*).



Note: The AirTouch 5 Main Module will provide power to the Smart AC Bridge over the cable when connected.

Powering up and Initializing

After verifying the connection between the units, power **ON** the **AirTouch 5 Main Module**, the **Smart AC Bridge** should also power **ON** and initialise (*RAPID L1 blinking*, *Blue*) then enter normal operation (*STEADY L1 blinking*, *Blue*).

What do the lights mean?	Г						·		
L1 Flash Every 0.2sec	Initialising		Bridge						
L1 Flash Every 0.5sec	Normal Operation			•					
L2 On	Data Transmission			L1	L2	L3			
L3 Steady Red	WiFi Not Paired			\bigcirc	0	0			
L3 Steady Green	WiFi Paired								
L3 Red & Green Flashing Alternatively	WiFi Lost	[
L1, L2, L3 Blue, Yellow, Green for 2sec	Bridge Reset	I							

Note: If **Smart AC Bridge** has not powered **ON**, please ensure the cable is securely connected to the **'RJ12'** and **'HomeKit'** ports for each device and check that the **AirTouch 5 Main Module** is powered **ON**.

Verifying Connection on AirTouch 5 Console

From your **AirTouch 5 Console** *Home Screen*, press the *Quick Menu* (top right) then navigate to *Options* page *(Settings > Options)*, there should now be a new selection button named *AC Bridge*.



Next Steps

For information on how to access and control your **AirTouch 5** system through **Apple Home**, please see: <u>Smart AC Bridge - Apple Home Set-Up</u>.

Support

For support please follow this link: <u>airtouch.net.au/support/</u>







airtouch.net.au

airtouch.net.au/support/

Version 1.0 January 2025 © Polyaire Pty Ltd